

### Setup Nokia Internet Telephone edition

The following instruction will guide you through the setting up of the most Nokia Symbian smart-phones supported Internet Telephone mobile phone, to **xol** network.

#### Creating or Editing SIP profiles

Select Menu > Tools > Settings > Connection > SIP settings > Options > Add new or Edit.



Edit your configuration like the following:

The screenshot shows a mobile configuration interface for a SIP profile. At the top, there is a blue header with a wrench icon and the profile name 'xol'. Below the header, several settings are listed with corresponding dropdown menus or buttons:

- Profile name: xol
- Service profile: IETF
- Default access point: LevelOne
- Public user name: 400XXXX@aloha
- Use compression: No
- Registration: always on
- Use security: No
- Proxy server: (empty field)
- Registrar server: (empty field)

At the bottom of the screen, there are two buttons: 'Options' on the left and 'Back' on the right.

- ▣ Profile name — Enter our network name: **xol**
- ▣ Service profile — Select **IETF**
- ▣ Default access point — Select the access point to use for the Internet connection. If no access point was define, see [instruction for setting up a WI-FI connection](#).
- ▣ Public user name — Enter your **Number** which you received from **xol (aloha line)** during registration to the service. For example if the **Number** is **4001234**, then type the following: **4001234@aloha**  
**(no need to enter sip: it added automatically)**
- ▣ Use compression — Select **No**
- ▣ Registration — Select **always on** (note for the user: you can choose "always on" your mobile will try to find any available AP and try to registered. This action will cost short battery life)
- ▣ Use security — Select **No**

Select Proxy server, to enter the proxy server Settings for this SIP profile.

Proxy server

Proxy server address  
208.87.169.82

Realm  
208.87.169.82

User name  
1234567

Password  
\*\*\*\*

Allow loose routing  
Yes

Transport type  
Auto

Port  
5060

Options Back

- ❑ Proxy server address - Enter the following address: **208.87.169.82** ("sip:" will be added automatically by the phone)
- ❑ Realm - Enter the following address: **208.87.169.82**
- ❑ User name - Enter your user name for example: 1234567
- ❑ Password - Enter you password which you received during the registration: 7654321
- ❑ Allow loose routing - Select: Yes
- ❑ Transport type - Select: Auto
- ❑ Port - Enter port number: 5060

Select Back Or Select Menu > Tools > Settings > Connection > SIP settings > Options > Add new or Edit > Registrar server to edit the registration servers

Regist. server

Registrar serv. addr.  
208.87.169.82

Realm  
208.87.169.82

User name  
1234567

Password  
\*\*\*\*

Transport type  
Auto

Port  
5060

Options Back

Select Registrar server - Enter the registration server settings for this SIP profile

- ❑ Registrar serv. Addr.- Enter the following address: **208.87.169.82** ("sip:" will be added automatically by the phone)
- ❑ Realm - Enter the following address: **208.87.169.82**
- ❑ User name - Enter your user name For example: 1234567
- ❑ Password - Enter you password which you received during the registration 7654321
- ❑ Transport type - Select:UDP
- ❑ Port - Enter port number: 5060

Select Back three times, Or Select Menu > Tools > Settings > Connection — to set the internet telephony settings.



Select Internet tel. settings - to set the Internet telephony network.

Select **xol**

Name - Enter the following name **xol** and Press OK

- ▣ SIP profiles - Select **xol** - and Press OK
- ▣ Press **ok**

press back three times, or select , Menu > Tools > Settings until you reach the setting window

**Select Call to set some of the calling features.**

Scroll through the different settings to configure the following features:

- ▣ Name - Enter the following name **xol**
- ▣ Send my net call ID - Select YES
- ▣ Internet call waiting - Select Activated
- ▣ Internet call alert - Select On
- ▣ Default call type - Select Internet (Note :Regardless of this setting, creating a call with the call key will automatically create a cellular call if the internet service is not available)

Press Back and Exit to return to the main screen.